

Analog Zero IF FM Decoder and Embodiments Thereof, Such as the Family Radio Service

Inventors: David F. Sorrells
Michael J. Bultman
Charles D. Clements
Robert W. Cook
Joseph M. Hamilla
Richard C. Looke
Charley D. Moses, Jr.
Gregory S. Silver

Cross-Reference to Other Applications

5
10
This application claims the benefit of U.S. Provisional Application No. 60/116,848, filed January 22, 1999, incorporated herein by reference in its entirety.

15
The following applications of common assignee are related to the present application, and are herein incorporated by reference in their entireties:

"Method and System for Down-Converting Electromagnetic Signals,"
Serial No. 09/176,022, filed on October 21, 1998.

20
"Method and System for Frequency Up-Conversion," Serial No. 09/176,154, filed on October 21, 1998.

"Method and System for Ensuring Reception of a Communications
Signal," Serial No. 09/176,415, filed on October 21, 1998.

25
"Integrated Frequency Translation and Selectivity," Serial No. 09/175,966,
filed on October 21, 1998.

"Image-Reject Down-Converter and Embodiments Thereof, Such as the
Family Radio Service," Serial No. *to be assigned*, Attorney Docket No.
1744.0240001, filed January 3, 2000.

Sub
al
anc

"Communication System With Multi-Mode and Multi-Band Functionality and Embodiments Thereof, Such as the Family Radio Service ," Serial No. *to be assigned*, Attorney Docket No. 1744.0260001, filed January 3, 2000.

"Multi-Mode, Multi-Band Communication System," Serial No. *to be assigned*, Attorney Docket No. 1744.0330001, filed January 3, 2000.

Background of the Invention

Field of the Invention

The present invention is generally directed toward receiver-transmitter systems referred to as Family Radio Service (FRS) units, although the invention is not limited to this embodiment. The Family Radio Service (FRS) is one of the Citizens Band Radio Services. It is intended for the use of family, friends, and associates to communicate among themselves within a neighborhood or while on group outings. There are fourteen discreet FRS channels available for use on a "take turns" basis. The FRS unit channel frequencies are:

<u>Channel No.</u>	<u>(MHz)</u>
1	462.5625
2	462.5875
3	462.6125
4	462.6375
5	462.6625
6	462.6875
7	462.7125
8	467.5625
9	467.5875
10	467.6125

11 467.6375
12 467.6625
13 467.6875
14 467.7125

5 Other selected technical specifications are:

- (a) Frequency modulation (although phase modulation is allowed);
- (b) Frequency tolerance of each FRS unit must be maintained within 0.00025%;
- (c) The authorized bandwidth for an FRS unit is 12.5 KHz; and
- (d) Effective radiated power (ERP) shall not, under any condition of modulation, exceed 0.500 W.

The operating rules for the FRS are found at 47 C.F.R. 95.191 - 95.194. For additional technical information, see 47 C.F.R. 95.601 - 95.669.

Related Art

A variety of FRS systems are available. Presently available FRS systems do not directly down-convert FM signals to demodulated baseband information signals.

What is needed is a method and system for directly down-converting FM signals to demodulated baseband information signals.

Summary of the Invention

5 The present invention is directed to a communications system comprising a method and system for directly down-converting FM signals to demodulated baseband information signals. The invention has a number of aspects, including a
10 ultra-low power down-converter and a high-efficiency transmitter and can be used to directly down-convert analog FM signals and digital FM signals to demodulated baseband information signals. In an embodiment, the present invention is used in a family radio service unit. It is to be understood, however, that the invention is not limited to this particular embodiment. Other
15 implementations in communications-related environments are within the scope and spirit of the invention.

In an embodiment, the invention includes aliasing an FM signal at an aliasing rate substantially equal to the frequency of the FM signal or substantially equal to a sub-harmonic thereof; adjusting the aliasing rate in accordance with
20 frequency changes on the FM signal to maintain the aliasing rate substantially equal to the frequency of the FM signal; and outputting a demodulated baseband information signal.

The invention includes an optional step of compensating for phase delays and/or other characteristics of the loop in order to maintain bandwidth and
25 stability for the loop.

In an embodiment, the invention is implemented as a zero IF FM decoder that down-converts an FM signal as an I and Q pair, sums the I and Q pair, and generates a correction signal from the sum. The correction signal is used to adjust the aliasing rate to continually alias the FM signal at a sub-harmonic of the FM
30 signal - even as the FM signal changes frequency.

In an embodiment, the invention is implemented as an ultra-low power down-converter. In an embodiment, the invention is implemented as a transceiver, which can be an FRS transceiver.

Advantages of the invention include, but are not limited to, power reduction, parts reduction, price reduction, size reduction, performance increase, efficiency, and integration possibilities.

Brief Description of the Figures

FIG. 1 is a high level block diagram of an ultra-low power down-converter in accordance with the present invention.

FIG. 2 is a schematic diagram of an exemplary implementation of the ultra-low power down-converter illustrated in FIG. 1.

FIG. 3 is a detailed block diagram of an aliasing module (i.e., universal frequency translator), in accordance with the present invention.

FIG. 4 illustrates a process for directly down-converting an FM signal to a demodulated baseband information signal.

FIG. 5 is a block diagram of an exemplary zero IF FM decoder for implementing the process of FIG. 4.

FIG. 6A is a timing diagram of an exemplary FM signal.

FIG. 6B is a timing diagram of an exemplary first aliasing signal, in accordance with the present invention.

FIG. 6C is a timing diagram of an exemplary second aliasing signal, in accordance with the present invention.

FIG. 6D is a timing diagram of exemplary down-converted signals and a summation signal, in accordance with the present invention.

FIG. 6E illustrates an exemplary control signal for controlling an aliasing rate for directly down-converting an FM signal to a demodulated baseband information signal, in accordance with the present invention.

FIG. 7 is a schematic diagram of an exemplary implementation of a summing module, an integration module and an optional loop compensation module, in accordance with the present invention.

FIG. 8 is a block diagram of a system for transmitting a voice signal, in accordance with an aspect of the present invention.

FIG. 9 is block diagram of a Universal Frequency Translator (UFT) in accordance with an aspect of the present invention.

FIG. 10 is a schematic diagram of an exemplary implementation of the system for transmitting a voice signal illustrated in FIG. 8.

FIG. 11 illustrates a field effect transistor (FET) that can be used by the present invention.

Detailed Description of the Preferred Embodiments

Family Radio with Zero IF FM Decoder

U.S. Patent Application 09/176,022, titled, "Method and System for Down-Converting Electromagnetic Signals," (hereinafter referred to as the '022 application) incorporated herein by reference in its entirety, discloses methods and systems for directly down-converting EM signals.

The '022 application discloses, among other things, how modulated EM signals can be directly down-converted to demodulated baseband information signals (also referred to interchangeably herein as direct to data or D2D

embodiments). For example, amplitude modulated (AM) signals and phase modulated (PM) signals can be directly down-converted to demodulated baseband information signals by aliasing the AM and PM signals at sub-harmonics of the AM and PM signals.

Frequency modulated (FM) signals, however, pose special challenges. For example, the '022 application discloses how frequency shift keying (FSK) signals, when aliased at fixed sub-harmonic, are down-converted to amplitude shift keying signals or to phase shift keying (PSK) signals. FM signals, unlike AM and PM signals, are not necessarily directly down-converted to demodulated baseband information signals by aliasing at a fixed sub-harmonic.

The present invention is a method and system for directly down-converting FM signals to demodulated baseband information signals.

FIG. 4 is a flowchart 402 that illustrates a method for directly down-converting FM signals to demodulated baseband information signals. FIG. 5 illustrates an exemplary embodiment of a zero IF FM decoder 502, which can be used to implement the process illustrated in the flowchart 402. The process illustrated in the flowchart 402 is not, however, limited to the zero IF FM decoder 502. Upon reading this disclosure, one skilled in the relevant art(s) will recognize that the process illustrated in the flowchart 402 can be practiced by other systems as well.

The zero IF FM decoder 502 includes a first aliasing module 510 and a second aliasing module 512. Preferably, the first and second aliasing modules 510 and 512 are implemented as disclosed in the '022 application and may be optimized as illustrated in FIGS. 1-3 of the present application and as described above. Other components of the zero IF FM decoder 502 are described below with the description of the process flowchart 402.

The process begins at step 410, which includes aliasing an FM signal at an aliasing rate substantially equal to the frequency of the FM signal or substantially equal to a sub harmonic thereof.

5
Sub
alt

10

In FIG. 5, step 410 is performed by the first and second aliasing module 510 and 512. The first aliasing module 510 receives an FM signal 514 and a first LO signal 516. The first LO signal 516 is substantially equal to the frequency of the FM signal 514 or a sub-harmonic thereof. Details of maintaining the LO signal 516 at the frequency of the FM signal 514, or a sub-harmonic thereof, is described in connection with step 412 below. The first aliasing module 510 uses the first LO signal 516 to down-convert the FM signal 514 to a first down-converted signal 518, as disclosed in the '022 application.

15

The second aliasing module 512 also receives the FM signal 514 and a second LO signal 520. The first LO signal 516 and the second LO signal 520 are substantially similar except that one is shifted in phase relative to the other. This is performed by, for example, a phase shifter 524. A variety of implementations of the phase shifter 524 suitable for the present invention are available as will be apparent to persons skilled in the relevant art, based on the teachings herein.

Sub
alt
2007

In an exemplary embodiment, the first and second LO signals 516 and 520 are separated by $\frac{1}{4}$ period of the FM signal 514, or any multiple of a period of the FM signal 514 plus $\frac{1}{4}$ period. Other phase differences are contemplated and are within the scope of the present invention. The second aliasing module 512 uses the second LO signal 520 to down-convert the FM signal 514 to a second down-converted signal 522, as disclosed in the '022 application.

25

Step 412 includes adjusting the aliasing rate in accordance with frequency changes on the FM signal to maintain the aliasing rate substantially equal to the frequency of the FM signal.

Sub
alt

The '022 application teaches that, so long as an aliasing rate remains substantially equal to the frequency of an FM signal, the resultant down-converted

50
Cone
signal is substantially a constant level. In the case of the zero IF FM decoder 502, therefore, the first and second down-converted signals 518 and 522 should generally be constant signals.

5 In order to maintain this condition, the zero IF FM decoder 502 maintains the phase of the aliasing signal 538 so that the phase of one of the aliasing signals 516 or 520 slightly leads the FM signal 514 while phase of the other aliasing signal slightly lags the FM signal 514.

As a result, one of the down-converted signals 518 or 522 is a constant level above DC while the other down-converted signal is a constant level below DC. The sum of the down-converted signals 518 and 522 is thus substantially zero. Summation of the down-converted signals 518 and 522 is performed by a summing module 526, which outputs a summation signal 536.

When summation signal 536 tends away from zero, it indicates that the frequency of the FM signal 514 is changing. The summation signal 536 is integrated by an integrator module 528, which outputs a control signal 532. The control signal 532 controls a voltage controlled oscillator (VCO) 534, which outputs the aliasing signal 538. The integrator maintains the control signal at a level necessary to insure that the FM signal 514 is aliased at a sub harmonic of the FM signal - even as the FM signal 514 changes frequency.

20 FIG. 7 illustrates, among other things, exemplary implementation details of the summing module 526 and the integrator module 528. A variety of other implementations of the summing module 526 and the integrator module 528, suitable for the present invention, are available, as will be apparent to persons skilled in the relevant art, based on the teachings herein. A variety of
25 implementations of the VCO 534 suitable for the present invention are also available as will be apparent to persons skilled in the relevant art, based on the teachings herein.

FIGS. 6A-6D illustrate exemplary timing diagrams for the above description. FIG. 6A illustrates an exemplary FM signal 514. FIG. 6B illustrates a first aliasing signal 612, which is generated within the first aliasing module 510 from the first LO signal 516. FIG. 6C illustrates a second aliasing signal 614, which is generated within the second aliasing module 512 from the second LO signal 520. The first and second aliasing signals 612 and 614 are separated by approximately $\frac{1}{4}$ period of the FM signal 514.

In operation, the first LO signal 612 aliases the FM signal 514 at approximately the same positive position on successive periods. The result is illustrated in FIG. 6D as down-converted signal 518. Similarly, the second LO signal 614 aliases the FM signal 514 at approximately the same negative position on successive periods. The result is illustrated in FIG. 6D as down-converted signal 522. FIG. 6D illustrates the sum of the down-converted signals 518 and 522 as summation signal 536.

When the frequency of the FM signal 514 changes, summation signal 536 tends away from zero. When this happens, the output of the integrator module 528 - i.e., control signal 532 - changes accordingly so that the VCO 534 changes the aliasing rate of the aliasing signal 538 so that the sum of the down-converted signals 518 and 520, summation signal 536, is maintained at zero. Thus, the control signal 532 changes in proportion to frequency changes on the FM signal 514. The changes on the FM signal 514 form a demodulated baseband information signal, which represents the information that had been frequency modulated on the FM signal 514.

In other words, as the frequency of the FM signal 514 changes, the integrator module 528 changes the control signal 532 to track and follow the deviation. This will reproduce – within the bandwidth of the loop – any arbitrary wave form, including analog and digital.

Another way of explaining it is to say that the invention tracks frequency changes on the FM signal by aliasing the FM signal at a sub-harmonic of the FM signal, adjusting the aliasing rate as necessary to maintain the aliasing rate at the sub-harmonic - even as the FM signal changes frequency.

5 In this way, the aliasing rate changes in proportion to frequency changes on the FM signal. Thus, changes to the aliasing rate are directly indicative of the information modulated on the FM signal. In the exemplary embodiment of FIG. 5, changes to the aliasing rate are indicated by the control voltage 532, which controls the VCO 534, which determines the aliasing rate.

10 FIG. 6E illustrates an exemplary control signal 532 for controlling the aliasing rate for directly down-converting the exemplary FM signal 514 illustrated in FIG. 6A to a demodulated baseband information signal. In this example, the control signal 532 has a first amplitude during time T1, when the FM signal 514 is at a first frequency. The control signal 532 has a second amplitude during time T2, when the FM signal 514 is at a second frequency. The control signal 532 reverts to the first amplitude during time T3, when the FM signal 514 returns to the first frequency. One skilled in the relevant art(s) will recognize, based on the disclosure herein, that the timing diagrams of FIGS. 6A-6E are exemplary illustrations of the invention. Other timing diagrams will apply for different
15
20 situations, all of which are within the scope of the present invention.

Step 414 includes outputting a demodulated baseband information signal. In FIG. 5, this is performed by outputting the control signal 532 as a demodulated baseband information signal

25 An optional step 416 includes compensating for phase delays and/or other characteristics of the loop in order to maintain bandwidth and stability for the loop. In FIG. 5, step 416 is performed by an optional loop compensator module 530. FIG. 7 illustrates exemplary implementation details of the loop compensation module 530. A variety of other loop compensation modules

suitable for the present invention are available as will be apparent to persons skilled in the relevant art, based on the teachings herein.

In an embodiment, a zero IF FM decoder as described above is implemented in an FRS.

5 Other advantages of the zero IF FM decoder include tuning reduction, parts reduction, price reduction, size reduction, performance increase, low frequency and power LO, and excellent linearity. Another advantage is that it can down-convert EM signals as high as 3.5 GHz when implemented in CMOS. Higher frequencies can be down-converted using other materials such as GaAs, for example.

Exemplary Environment: Ultra-Low Power Down-Converter

10
15 The present invention can be implemented with an aliasing system as disclosed in U.S. Patent Application 09/176,022, titled, "Method and System for Down-Converting Electromagnetic Signals," (hereinafter referred to as the '022 application) incorporated herein by reference in its entirety.

FIG. 1 illustrates an exemplary aliasing system 100 for down-converting electromagnetic (EM) signals, such as an RF input (RF_{in}) signal 102. The aliasing system 100 is an exemplary embodiment of an optimized aliasing system, referred to herein as an ultra low power down-converter.

20 The exemplary aliasing system 100 includes an aliasing module 110 that aliases an EM signal 112, using an aliasing signal 114, and outputs a down-converted signal 116, as disclosed in U.S. Patent Application 09/176,022, titled, "Method and System for Down-Converting Electromagnetic Signals," (hereinafter referred to as the '022 application) incorporated herein by reference in

its entirety. The aliasing module 110 is also referred to herein as a universal frequency translator (UFT) module.

Aliasing system 100 optionally includes one or more of an input impedance match module 118, a parallel resonant tank module 120, and an output impedance match module 122, as disclosed in the '022 application.

Aliasing system 100 optionally includes a local oscillator (LO) impedance match module 124 for impedance matching a local oscillator input (LO_{in}) signal 126, generated by a local oscillator 128, to the aliasing module 110. The LO impedance match module 124 can be designed to increase the voltage of the LO_{in} signal 126, as illustrated by a higher voltage LO_{in} signal 130. The LO impedance match module 124 permits the aliasing system 100 to efficiently operate with a relatively low voltage LO_{in} signal 126, without the use of power consuming amplifiers that would otherwise be necessary to increase the amplitude of the LO_{in} signal 126.

Unless otherwise noted, the aliasing signal 114 is used interchangeably herein to refer to the LO_{in} signal 126 and/or the higher voltage LO_{in} signal 130.

The aliasing system 100 optionally includes a DC block 132 that substantially blocks DC while passing substantially all non-DC. In the exemplary embodiment, the DC block 132 is a DC blocking capacitor 133. A variety of implementations of the DC block 132 suitable for the present invention are available as will be apparent to persons skilled in the relevant art, based on the teachings herein.

The aliasing system 100 optionally includes a bias module 134 for biasing the aliasing signal 114. A variety of implementations of the biasing module 134 suitable for the present invention are available as will be apparent to persons skilled in the relevant art, based on the teachings herein.

FIG. 2 illustrates an exemplary schematic diagram 202 that can be used to implement the aliasing system 100. The exemplary schematic diagram 202 provides exemplary circuit elements that can be used within the optional input impedance match module 118, the optional parallel resonant tank 120, the optional output impedance match module 122, the optional LO impedance match module, the optional DC block 132, and the optional bias module 134. The invention is not limited to the exemplary embodiment of FIG. 2.

Sub 0127
The exemplary schematic diagram 202 includes a storage module 210 for storing energy transferred from the EM signal 112, as disclosed in the '022 application.

In the schematic diagram 202, the aliasing module 110 of FIG. 1 is illustrated as an application specific integrated circuit (ASIC) 212. In an embodiment, the ASIC is implemented in complementary metal oxide semiconductor (CMOS).

15
The ASIC 212 is coupled to a first voltage source 218 for supplying power circuits within the ASIC 212. The circuits within the ASIC 212 are described below with reference to FIG. 3. An optional first bypass module 220 is optionally disposed as illustrated to substantially eliminate unwanted frequencies from the first power supply 218 and from the ASIC 212.

20
The ASIC 212 includes a substrate (not shown) which is optionally coupled to a second voltage source 214. An advantage of coupling the substrate to the second voltage source 214 is described below with reference to FIG. 3. When the substrate is coupled to the second voltage source 214, an optional second bypass module 216 is optionally disposed as illustrated to substantially eliminate unwanted frequencies from the substrate and the second voltage source 214.

Sub 0137
FIG. 3 illustrates an aliasing module 302, which is an exemplary embodiment of the aliasing module 110 and the ASIC 212. The aliasing module

302 includes a sine wave to square wave converter module 310, a pulse shaper module 312 and a switch module 314. The sine wave to square wave converter module 310 converts a sine wave 114 from the local oscillator 128 to a square wave 311. The pulse shaper module 312 receives the square wave 311 and generates energy transfer pulses 313 therefrom. Energy transfer pulses are discussed in greater detail in the '022 application.

In an embodiment, the pulse shaper module 312 is implemented as a mono-stable multi-state vibrator. A variety of implementations of the pulse shaper module 312 suitable for the present invention are available as will be apparent to persons skilled in the relevant art, based on the teachings herein.

Generally, the frequency of the energy transfer pulses 311 is determined by the frequency of the aliasing signal 114 and the width or aperture of the energy transfer pulses is determined by the pulse shaper module 312.

In the illustrated embodiment, where the sine wave to square wave converter module 310 and the pulse shaper module 312 are provided on-chip, the ASIC substrate (not shown) is optionally coupled to the second power supply 214. The second power supply 214 can be varied to affect the performance of the circuits on the ASIC 212, with a result of effectively adjusting the pulse width of the energy transfer pulses 313.

In an alternative embodiment, the sine wave to square wave converter module 310 and/or the pulse shaper module 312 are provided off-chip.

An advantage of the ultra-low power down-converter aliasing system 100 is its low power consumption. For example, in an actual implementation, the aliasing module 302 required an average of approximately 1 mA and consumed approximately 3 to 5 mWatt. This is significantly greater performance than conventional down converter systems.

Other advantages of the ultra-low power down-converter aliasing system 100 include tuning reduction, parts reduction, price reduction, size reduction, performance increase, low frequency and power LO, and excellent linearity. Another advantage of the ultra-low power down-converter aliasing system is that it can down-convert EM signals as high as 3.5 GHz when implemented in CMOS. Higher frequencies can be down-converted using other materials such as gallium arsenide (GaAs), for example.

In an embodiment, an ultra-low power down-converter as described above is implemented in an FRS.

High Efficiency Transmitter

This section describes the high-efficiency transmitter embodiment of a frequency up-converter for use in a family radio service unit. It describes methods and systems related to a transmitter. Structural exemplary embodiments for achieving these methods and systems are also described. It should be understood that the invention is not limited to the particular embodiments described below. Equivalents, extensions, variations, deviations, etc., of the following will be apparent to persons skilled in the relevant art(s) based on the teachings contained herein. Such equivalents, extensions, variations, deviations, etc., are within the scope and spirit of the present invention.

The present invention has significant advantages over conventional transmitters. These advantages include, but are not limited to, a reduction in the number of parts to accomplish the transmitter function, a reduction in the power requirements for the circuit, and a reduction of cost and complexity by permitting the use of circuits designed for lower frequency applications, including, but not limited to, lower frequency oscillators.

An embodiment for transmitting a voice signal is shown in FIG. 8. The voice signal is input to a microphone 802. The output of microphone 802 is an analog voice signal 824 which is connected to an audio amplifier 804. The output of audio amplifier 804 is an amplified signal 826 which is filtered by an audio buffer amplifier 806. Audio buffer amplifier 806 acts as a low pass filter to eliminate unwanted higher frequency signals. The output of audio buffer amplifier 806 is a signal 828 which is accepted by crystal oscillator 808. Crystal oscillator 808 operates as a voltage controlled oscillator and outputs a frequency modulated (FM) signal 830 that is a sinusoidal signal biased substantially around zero volts.

At a node 840, a bias voltage 810 combines with FM signal 830. For the implementation wherein bias voltage 810 is a positive voltage, the bias point of FM signal 830 is raised such that substantially the entire waveform is above zero. In an alternate implementation wherein bias voltage 810 is negative, the bias point of FM signal 830 is lowered such that substantially all of the waveform is below zero. This combination of FM signal 830 and bias voltage 810 results in an FM control signal 832. Substantially all of FM control signal 832 is above zero (or below zero if bias voltage 810 is negative). FM control signal 832 is then input to a universal frequency translator (UFT) module 812.

UFT module 812 is comprised of a pulse shaping circuit and a switch, and is described in detail below in FIG. 9. The output of UFT module 812 is a rectangular waveform 834 that contains a plurality of harmonics. Rectangular waveform 834 is accepted by a filter 816 which filters out the undesired harmonic frequencies and outputs a desired output signal 836. Desired output signal 836 is the frequency modulated signal at the desired output frequency. Desired output signal 836 goes to a driver 818 and then to a power amplifier 820. The output of power amplifier 820 is an amplified output signal 838. Amplified output signal 838 is ready for transmission and is routed to an antenna 822.

5 The design of UFT module 812 is shown in FIG. 9. FM control signal 832 is accepted by a "square-up" circuit 902 to create a frequency modulated square wave 908 from the sinusoidal waveform of FM control signal 832. FM square wave 908 is then routed to a pulse shaper 904 to create a string of pulses 910. In one embodiment, pulse shaper 904 is a mono-stable multi-vibrator. The string of pulses 910 operates a switch 906 which creates rectangular waveform 834. Typically, pulse shaper 904 is designed such that each pulse in string of pulses 910 has a pulse width " τ " that is substantially equal to $(n/2) \cdot T$, where " T " is the period of desired output signal 836, and " n " is any odd number. As stated previously, switch 906 outputs rectangular waveform 834, which is then routed to filter 816 of FIG. 8. Another input to UFT module 812 is a bias signal 814, which, in this embodiment, is connected to the opposite terminal of switch 906 from rectangular waveform 834.

10
15 *sub art*
20 In one implementation of the invention, switch 906 is a field effect transistor (FET). A specific implementation wherein the FET is a complementary metal oxide semiconductor (CMOS) FET is shown in FIG 11. A CMOS FET has three terminals: a gate 1102, a source 1104, and a drain 1106. String of pulses 910 is shown at gate 1102, bias signal 814 is shown at source 1104, and rectangular waveform 834 is shown at drain 1106. Those skilled in the relevant art(s) will appreciate that the source and drain of a FET are interchangeable, and that bias signal 814 could be at the drain 1106, with rectangular waveform 834 being at the source 1104. Numerous circuit designs are available to eliminate any possible asymmetry, and an example of such a circuit may be found in co-pending U.S. Patent Application 09/176,154, entitled "Method and System for Frequency Up-Conversion," filed October 21, 1998, the full disclosure of which is
25 incorporated herein by reference.

FIG. 10 is a detailed schematic drawing of the embodiment described above. Those skilled in the relevant art(s) will appreciate that numerous circuit

designs can be used, and that FIG. 10 is shown for illustrative purposes only, and is not limiting. In addition, there are a variety of commercially available components and assemblies suitable for use in the present invention (e.g., audio amplifiers, audio buffer amplifiers, crystal oscillators, drivers, and power amplifiers) as will be apparent to those skilled in the relevant art(s) based on the teachings contained herein.

Microphone 802 of FIG. 8 is shown as a microphone 1002 in FIG. 10. The output of microphone 1002 is a voice signal which is routed to an audio amplifier 1004 and then to an audio buffer amplifier 1006. A crystal oscillator 1008 is driven by the output of audio buffer amplifier 1006 to create the FM signal 830. A bias voltage 1010 combines with FM signal 830 to create the FM control signal 832. FM control signal 832 is routed to a UFT module 1012 which creates rectangular signal 834. Also connected to UFT 1012 is a bias signal 1012. Rectangular signal 834 is filtered by a filter 1016 to remove the unwanted harmonics and results in desired output signal 836. Desired output signal 836 goes to a driver 1018 and then to a power amplifier 1020. The output of power amplifier 1020 is amplified output signal 838. Amplified output signal 838 is ready for transmission and is routed to an antenna 1022.

In the above implementation, looking back to FIG. 8, the frequency of FM control signal 832 is a sub-harmonic of the frequency of desired output signal 836. It will be understood by those skilled in the relevant art(s) that the selection of the frequencies will have an impact on the amplitude of the desired output signal 836, and will be a determinative factor as to whether or not driver 818 and/or power amplifier 820 will be needed. Similarly, those skilled in the relevant art(s) will understand that the selection of microphone 802 will have an effect on analog voice signal 824, and will be a determinative factor as to whether or not audio amplifier 804 and/or audio buffer amplifier 806 will be needed. Additionally, those skilled in

the relevant art(s) will understand that the specific design of UFT 812 will be a determinative factor as to whether or not bias voltage 810 is needed.

5 The invention described above is for an embodiment wherein the output of the microphone is described as an analog voice signal. Those skilled in the relevant art(s) will understand that the invention applies equally to a digital signal, either digital data or a voice signal that has been digitized.

Transceiver

10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995
1000
1005
1010
1015
1020
1025
1030
1035
1040
1045
1050
1055
1060
1065
1070
1075
1080
1085
1090
1095
1100
1105
1110
1115
1120
1125
1130
1135
1140
1145
1150
1155
1160
1165
1170
1175
1180
1185
1190
1195
1200
1205
1210
1215
1220
1225
1230
1235
1240
1245
1250
1255
1260
1265
1270
1275
1280
1285
1290
1295
1300
1305
1310
1315
1320
1325
1330
1335
1340
1345
1350
1355
1360
1365
1370
1375
1380
1385
1390
1395
1400
1405
1410
1415
1420
1425
1430
1435
1440
1445
1450
1455
1460
1465
1470
1475
1480
1485
1490
1495
1500
1505
1510
1515
1520
1525
1530
1535
1540
1545
1550
1555
1560
1565
1570
1575
1580
1585
1590
1595
1600
1605
1610
1615
1620
1625
1630
1635
1640
1645
1650
1655
1660
1665
1670
1675
1680
1685
1690
1695
1700
1705
1710
1715
1720
1725
1730
1735
1740
1745
1750
1755
1760
1765
1770
1775
1780
1785
1790
1795
1800
1805
1810
1815
1820
1825
1830
1835
1840
1845
1850
1855
1860
1865
1870
1875
1880
1885
1890
1895
1900
1905
1910
1915
1920
1925
1930
1935
1940
1945
1950
1955
1960
1965
1970
1975
1980
1985
1990
1995
2000
2005
2010
2015
2020
2025
2030
2035
2040
2045
2050
2055
2060
2065
2070
2075
2080
2085
2090
2095
2100
2105
2110
2115
2120
2125
2130
2135
2140
2145
2150
2155
2160
2165
2170
2175
2180
2185
2190
2195
2200
2205
2210
2215
2220
2225
2230
2235
2240
2245
2250
2255
2260
2265
2270
2275
2280
2285
2290
2295
2300
2305
2310
2315
2320
2325
2330
2335
2340
2345
2350
2355
2360
2365
2370
2375
2380
2385
2390
2395
2400
2405
2410
2415
2420
2425
2430
2435
2440
2445
2450
2455
2460
2465
2470
2475
2480
2485
2490
2495
2500
2505
2510
2515
2520
2525
2530
2535
2540
2545
2550
2555
2560
2565
2570
2575
2580
2585
2590
2595
2600
2605
2610
2615
2620
2625
2630
2635
2640
2645
2650
2655
2660
2665
2670
2675
2680
2685
2690
2695
2700
2705
2710
2715
2720
2725
2730
2735
2740
2745
2750
2755
2760
2765
2770
2775
2780
2785
2790
2795
2800
2805
2810
2815
2820
2825
2830
2835
2840
2845
2850
2855
2860
2865
2870
2875
2880
2885
2890
2895
2900
2905
2910
2915
2920
2925
2930
2935
2940
2945
2950
2955
2960
2965
2970
2975
2980
2985
2990
2995
3000
3005
3010
3015
3020
3025
3030
3035
3040
3045
3050
3055
3060
3065
3070
3075
3080
3085
3090
3095
3100
3105
3110
3115
3120
3125
3130
3135
3140
3145
3150
3155
3160
3165
3170
3175
3180
3185
3190
3195
3200
3205
3210
3215
3220
3225
3230
3235
3240
3245
3250
3255
3260
3265
3270
3275
3280
3285
3290
3295
3300
3305
3310
3315
3320
3325
3330
3335
3340
3345
3350
3355
3360
3365
3370
3375
3380
3385
3390
3395
3400
3405
3410
3415
3420
3425
3430
3435
3440
3445
3450
3455
3460
3465
3470
3475
3480
3485
3490
3495
3500
3505
3510
3515
3520
3525
3530
3535
3540
3545
3550
3555
3560
3565
3570
3575
3580
3585
3590
3595
3600
3605
3610
3615
3620
3625
3630
3635
3640
3645
3650
3655
3660
3665
3670
3675
3680
3685
3690
3695
3700
3705
3710
3715
3720
3725
3730
3735
3740
3745
3750
3755
3760
3765
3770
3775
3780
3785
3790
3795
3800
3805
3810
3815
3820
3825
3830
3835
3840
3845
3850
3855
3860
3865
3870
3875
3880
3885
3890
3895
3900
3905
3910
3915
3920
3925
3930
3935
3940
3945
3950
3955
3960
3965
3970
3975
3980
3985
3990
3995
4000
4005
4010
4015
4020
4025
4030
4035
4040
4045
4050
4055
4060
4065
4070
4075
4080
4085
4090
4095
4100
4105
4110
4115
4120
4125
4130
4135
4140
4145
4150
4155
4160
4165
4170
4175
4180
4185
4190
4195
4200
4205
4210
4215
4220
4225
4230
4235
4240
4245
4250
4255
4260
4265
4270
4275
4280
4285
4290
4295
4300
4305
4310
4315
4320
4325
4330
4335
4340
4345
4350
4355
4360
4365
4370
4375
4380
4385
4390
4395
4400
4405
4410
4415
4420
4425
4430
4435
4440
4445
4450
4455
4460
4465
4470
4475
4480
4485
4490
4495
4500
4505
4510
4515
4520
4525
4530
4535
4540
4545
4550
4555
4560
4565
4570
4575
4580
4585
4590
4595
4600
4605
4610
4615
4620
4625
4630
4635
4640
4645
4650
4655
4660
4665
4670
4675
4680
4685
4690
4695
4700
4705
4710
4715
4720
4725
4730
4735
4740
4745
4750
4755
4760
4765
4770
4775
4780
4785
4790
4795
4800
4805
4810
4815
4820
4825
4830
4835
4840
4845
4850
4855
4860
4865
4870
4875
4880
4885
4890
4895
4900
4905
4910
4915
4920
4925
4930
4935
4940
4945
4950
4955
4960
4965
4970
4975
4980
4985
4990
4995
5000
5005
5010
5015
5020
5025
5030
5035
5040
5045
5050
5055
5060
5065
5070
5075
5080
5085
5090
5095
5100
5105
5110
5115
5120
5125
5130
5135
5140
5145
5150
5155
5160
5165
5170
5175
5180
5185
5190
5195
5200
5205
5210
5215
5220
5225
5230
5235
5240
5245
5250
5255
5260
5265
5270
5275
5280
5285
5290
5295
5300
5305
5310
5315
5320
5325
5330
5335
5340
5345
5350
5355
5360
5365
5370
5375
5380
5385
5390
5395
5400
5405
5410
5415
5420
5425
5430
5435
5440
5445
5450
5455
5460
5465
5470
5475
5480
5485
5490
5495
5500
5505
5510
5515
5520
5525
5530
5535
5540
5545
5550
5555
5560
5565
5570
5575
5580
5585
5590
5595
5600
5605
5610
5615
5620
5625
5630
5635
5640
5645
5650
5655
5660
5665
5670
5675
5680
5685
5690
5695
5700
5705
5710
5715
5720
5725
5730
5735
5740
5745
5750
5755
5760
5765
5770
5775
5780
5785
5790
5795
5800
5805
5810
5815
5820
5825
5830
5835
5840
5845
5850
5855
5860
5865
5870
5875
5880
5885
5890
5895
5900
5905
5910
5915
5920
5925
5930
5935
5940
5945
5950
5955
5960
5965
5970
5975
5980
5985
5990
5995
6000
6005
6010
6015
6020
6025
6030
6035
6040
6045
6050
6055
6060
6065
6070
6075
6080
6085
6090
6095
6100
6105
6110
6115
6120
6125
6130
6135
6140
6145
6150
6155
6160
6165
6170
6175
6180
6185
6190
6195
6200
6205
6210
6215
6220
6225
6230
6235
6240
6245
6250
6255
6260
6265
6270
6275
6280
6285
6290
6295
6300
6305
6310
6315
6320
6325
6330
6335
6340
6345
6350
6355
6360
6365
6370
6375
6380
6385
6390
6395
6400
6405
6410
6415
6420
6425
6430
6435
6440
6445
6450
6455
6460
6465
6470
6475
6480
6485
6490
6495
6500
6505
6510
6515
6520
6525
6530
6535
6540
6545
6550
6555
6560
6565
6570
6575
6580
6585
6590
6595
6600
6605
6610
6615
6620
6625
6630
6635
6640
6645
6650
6655
6660
6665
6670
6675
6680
6685
6690
6695
6700
6705
6710
6715
6720
6725
6730
6735
6740
6745
6750
6755
6760
6765
6770
6775
6780
6785
6790
6795
6800
6805
6810
6815
6820
6825
6830
6835
6840
6845
6850
6855
6860
6865
6870
6875
6880
6885
6890
6895
6900
6905
6910
6915
6920
6925
6930
6935
6940
6945
6950
6955
6960
6965
6970
6975
6980
6985
6990
6995
7000
7005
7010
7015
7020
7025
7030
7035
7040
7045
7050
7055
7060
7065
7070
7075
7080
7085
7090
7095
7100
7105
7110
7115
7120
7125
7130
7135
7140
7145
7150
7155
7160
7165
7170
7175
7180
7185
7190
7195
7200
7205
7210
7215
7220
7225
7230
7235
7240
7245
7250
7255
7260
7265
7270
7275
7280
7285
7290
7295
7300
7305
7310
7315
7320
7325
7330
7335
7340
7345
7350
7355
7360
7365
7370
7375
7380
7385
7390
7395
7400
7405
7410
7415
7420
7425
7430
7435
7440
7445
7450
7455
7460
7465
7470
7475
7480
7485
7490
7495
7500
7505
7510
7515
7520
7525
7530
7535
7540
7545
7550
7555
7560
7565
7570
7575
7580
7585
7590
7595
7600
7605
7610
7615
7620
7625
7630
7635
7640
7645
7650
7655
7660
7665
7670
7675
7680
7685
7690
7695
7700
7705
7710
7715
7720
7725
7730
7735
7740
7745
7750
7755
7760
7765
7770
7775
7780
7785
7790
7795
7800
7805
7810
7815
7820
7825
7830
7835
7840
7845
7850
7855
7860
7865
7870
7875
7880
7885
7890
7895
7900
7905
7910
7915
7920
7925
7930
7935
7940
7945
7950
7955
7960
7965
7970
7975
7980
7985
7990
7995
8000
8005
8010
8015
8020
8025
8030
8035
8040
8045
8050
8055
8060
8065
8070
8075
8080
8085
8090
8095
8100
8105
8110
8115
8120
8125
8130
8135
8140
8145
8150
8155
8160
8165
8170
8175
8180
8185
8190
8195
8200
8205
8210
8215
8220
8225
8230
8235
8240
8245
8250
8255
8260
8265
8270
8275
8280
8285
8290
8295
8300
8305
8310
8315
8320
8325
8330
8335
8340
8345
8350
8355
8360
8365
8370
8375
8380
8385
8390
8395
8400
8405
8410
8415
8420
8425
8430
8435
8440
8445
8450
8455
8460
8465
8470
8475
8480
8485
8490
8495
8500
8505
8510
8515
8520
8525
8530
8535
8540
8545
8550
8555
8560
8565
8570
8575
8580
8585
8590
8595
8600
8605
8610
8615
8620
8625
8630
8635
8640
8645
8650
8655
8660
8665
8670
8675
8680
8685
8690
8695
8700
8705
8710
8715
8720
8725
8730
8735
8740
8745
8750
8755
8760
8765
8770
8775
8780
8785
8790
8795
8800
8805
8810
8815
8820
8825
8830
8835
8840
8845
8850
8855
8860
8865
8870
8875
8880
8885
8890
8895
8900
8905
8910
8915
8920
8925
8930
8935
8940
8945
8950
8955
8960
8965
8970
8975
8980
8985
8990
8995
9000
9005
9010
9015
9020
9025
9030
9035
9040
9045
9050
9055
9060
9065
9070
9075
9080
9085
9090
9095
9100
9105
9110
9115
9120
9125
9130
9135
9140
9145
9150
9155
9160
9165
9170
9175
9180
9185
9190
9195
9200
9205
9210
9215
9220
9225
9230
9235
9240
9245
9250
9255
9260
9265
9270
9275
9280
9285
9290
9295
9300
9305
9310
9315
9320
9325
9330
9335
9340
9345
9350
9355
9360
9365
9370
9375
9380
9385
9390
9395
9400
9405
9410
9415
9420
9425
9430
9435
9440
9445
9450
9455
9460
9465
9470
9475
9480
9485
9490
9495
9500
9505
9510
9515
9520
9525
9530
9535
9540
9545
9550
9555
9560
9565
9570
9575
9580
9585
9590
9595
9600
9605
9610
9615
9620
9625
9630
9635
9640
9645
9650
9655
9660
9665
9670
9675
9680
9685
9690
9695
9700
9705
9710
9715
9720
9725
9730
9735
9740
9745
9750
9755
9760
9765
9770
9775
9780
9785
9790
9795
9800
9805
9810
9815
9820
9825
9830
9835
9840
9845
9850
9855
9860
9865
9870
9875
9880
9885
9890
9895
9900
9905
9910
9915
9920
9925
9930
9935
9940
9945
9950
9955
9960
9965
9970
9975
9980
9985
9990
9995
10000
10005
10010
10015
10020
10025
10030
10035
10040
10045
10050
10055
10060
10065
10070
10075
10080
10085
10090
10095
10100
10105
10110
10115
10120
10125
10130
10135
10140
10145
10150
10155
10160
10165
10170
10175
10180
10185
10190
10195
10200
10205
10210
10215
10220
10225
10230
10235
10240